

Works with

\* Sauter ATI \* T&A Barber coleman

\* TEG Honeywell


\* Others .lohnson Landisgyr Staefa


Satchwell

# Temp. detector, Surface

Pt 1000 Ω sensor,range;0...130 C with resistance standard signal output **TDS23.122** 

### TDS23.1230 B Standard type





### Description

Electronic temperature detector is used to control of temperature in a pipe or in a vessel of any medium in a conditioning system, this detected value can also be used as a reference signal to building automation system.

Application

In heating, ventilating, air conditioning and other industrial installations for control and receiving reference signals in a pipe or in vessel.

Compact design of the detector is ideal for maintenance or replacement without any special tools. This signal gives also very accurate information in a flow circuit of any medium to the DDC data acquisition unit requiring comparatively short distance cabling system connected to computerized data acquisition system by communication like Building Automation System.

**Ordering Specification** 

When ordering, please give full designation and type reference of unit:

Ex: TDS23.1230A

Temperature detector for Surface 1000 output 1 output, 0... 130 C None power supply with 150mm clamping band

Standard stock type TDS23.1230AB

Ta	ch	ni	ca	ır	)at	2

Technical Data	Standard type
Permissible amb.temp.	-2565 <sup>0</sup> C
Operation Transport & storage	-1550 <sup>0</sup> C
Operating range	-2565 <sup>0</sup> C
Permissible amb.humid.	Class D to DIN 40040
Protection standard of housing	IP42
Cable entry glands	pg 11
Weight	0.1kg

#### Temperature sensor

Measuring range	0+150 <sup>0</sup> C 0+130 <sup>0</sup> C
Application range Measuring accuracy at 20 C Output signal	± 0.1% FS 1000 at 20 C

Permissible amb.humidity Permissible cable length Copper 0.6mm dia

Copper 1.0mm dia Copper 1.5mm dia 0...95% rH

35m 120m 320m

# Summary of

Type / Model	Temp Range	Plpe Dia. up to	
TDS23.1230B	0130 C	150mm	
TDS23.1130B	-3590 C	150mm	

#### **Function**

The detector senses temperature of the surface of pipe of tank wall by the positive thermal coefficient element, Pt1000 which gives linear changes of signal according to temperature of the surface. The change of resistance is being transferred directly to the terminals. This signal is good for comparatively short distance applications like connection to the DDC unit on site.

# The best in performance

In the thin pure copper film wrap over the sensing element and the leads connected to the plastics case for protection from short circuit. The detector is Ideal fro high pressure pipe line and retrofitting job which may be difficult in installing new pocket in to the pipe lines or tanks.

#### Optional units available


- An additional output signals are available in add on module:

### **Design Features**

External box is very compact and made of engineering plastics since it has only terminal and to prevent unwanted damage of electronics by the workers while installation at the job site. The sensing element is encased in a high impact engineering plastic tube. Mounting the detector and dismounting is very simple and easy since there is no need to disconnect the wiring and shut down the power supply for checking the units. there is no need of special tools nor adjustments.

Entirely Maintenance free PTC type sensing element.

#### Structure



### **Application Advice**

For further information on the complete detector unit also refer to the Data Sheet of the various type of detectors, P34000... P34999.

Observe the permissible temperatures. For details refer to <a href="#">Application > and <Technical Data></a>

Data Sheet 34001 contains basic system data on POLYTEK. All hints and explanations given in this sheet must be observed.

# **Mounting and Installation Advice**

Mounting positions:


When the detector has to be mounted on supply pipe the location of the detector must be kept between 3 to 8 meters from the heat exchanger unit.

For accurate control of the temperature

follow recommendation as;

-with Plate package; -with Shell & Tube:

between 3 to 8 meters between 1 to 5 meters



The detector mounting instructions are included in the delivery box together with products.

### **Commissioning Advice**


When commissioning the installation, check the wiring and temporarily filter tube.

# Wiring Diagram

Internal Diagram




# Connecting terminals



M = System neutral B = Temp.signal

#### **Dimensions**

#### TDS23,1230



Dimensions in mm

We reserve the right to make changes and improvements in our products which may affect the accuracy of the information contained in this leaflet.

Example: Given data: ΔP =0.35Bar and Kv = 13 a.Trace down the vertical line of 0.35 Bar of ΔP to an intersecting point with horizontal line of Kv flow rate of 13 m³/h.

b.Select Kv=19 of DN40 between the line of Kv =31 and the line of Kv=1 9

The answer is TYPE:VTF31.140;40mm(1-1/4") of Kv=19

# TYPE:VTF30... Pressure drop $\Delta P_{v100}$ in Bar 3000 2000 1000 800 600 400 300 **S00** 100 80 60 50 40 30 50 rate V<sub>100</sub> in M<sup>3</sup>/h 10 8 3 2 8.0 0.6 0.5 0.4 0.3 Noise limits Direct 5.0 Reverse 0.1 0.08 0.06 400 500 600 kPa 8 50 50 60 œ


9

4

Recommended selection in  $\triangle Pv100 = 0.3Bar$  $1m^3/h = 0.278kg/s$  water at  $20^{\circ}C$ 

0.5

50 00



DN mm	inch	A	В	С	D	F	н	L	ATI		s	Wgt kg	Suita ATI	L/G	tuators H/W
15 20 25 32 40 50 65 80 100 125 150 200	1/2" 3/4" 1" 11/4" 11/2" 2" 21/2" 3" 4" 5" 6" 8" 10"	100 100 160 200 230 230 290 310 350 400 480 600 720	50 80 100 100 115 145 155 175 200 240 305 370	100 100 115 150 165 185 200 220 250 285 345 400	10 10 16 18 18 20 20 22 24 26 26 29 29	12x 4 12x 4 14x 4 18x 4 18x 4 18x 4 18x 8 18x 8 18x 8 22x 8 22x12 22x12	96.5 96.5 96.5 96.5 96.5 96.5 96.5 116.5 116.5	26 26 34 39 39 60 60 91 102 118 124 150	44 44 44 44 44 44 44 44 44 44	35 35 35 35 35 35 35 35 35 35 35 35 35	10 10 10 10 10 10 10 14 14 14 16 16	4.2 5.9 10.1 10.1 15.5 17.3 22.9	AQX		M904+Q455 M904+Q455

Dimensions in mm